Item no.: 2060750



Presence and motion detectors Indoor detectors

Description

- Passive infra-red motion detector for wall installation
- Square detection area 170°, 14 x 17 m (238 m²)
- Without frame, adapter frames for common switch ranges available as accessory
- 1 channel light
- Fully or semi-automatic operation
- Adjustable brightness switching value, teach-in function
- Staircase light function
- Switch-on delay configurable
- Extension of detection area via master/slave switching
- Ready for immediate use due to factory presetting
- Restriction of detection area possible
- Mixed light measurement suitable for the control of fluorescent, incandescent, halogen lamps and LEDs
- Integrated button (can be blocked)
- Product design by ID AID



Technical data


	theMura S180-100 B UP	
Operating voltage	230 V AC	
Frequency	50 – 60 Hz	
Installation height	0.8 - 1.2 m	
Installation type	Flush-mounted wall installation	
Colour	White	
Switching output	Light	
Power consumption	~0.4 W	
Light measurement	Mixed light measurement	
Setting range brightness	5 – 1000 lx	
Light switch-off delay	10 s - 30 min/Impuls	
Lamps	Incandescent/halogen lamps, fluorescent lamps, Energy saving lamps, LEDs	

	theMura S180-100 B UP		
Incandescent/halogen lamp load	2300 W		
Inrush current	max. 600 A / 200 µs		
LED lamp < 2 W	40 W		
LED lamp 2-8 W	450 W		
LED lamp > 8 W	450 W		
Type of connection	Spring terminals		
Size of concealed housing	Ø 55 mm (NIS, PMI)		
Detection range	238 m² (14 x 17 m)		
Detection angle	170°		
Ambient temperature	-15°C 45°C		
Type of protection	IP 20		

Item no.: 2060750




Connection example



Detection range for planning applications at a temperature of 21 °C

Mounting height (A)	Head on to (R)	Diagonally (t)	Sitting (S)
1.2 m	120 m² 12 m x 10 m	238 m² 14 m x 17 m	







Item no.: 2060750




Scale drawings


theMura S180-100 UP WH (2060650) + theMura S180-101 UP WH (2060655)








theMura S180-100 UP (2060750) + theMura S180-101 B UP (2060755)





Accessories

Surface frame LUXA 103-200 Item no.: 9070504



Adapter frame 45A BJBSI WH Item no.: 9070788



Adapter frame 45A MMP WH Item no.: 9070790



Adapter frame 45A GS WH Item no.: 9070791



Item no.: 2060750



Accessories


Adapter frame 45A JAS WH Item no.: 9070789



Adapter frame 45A BS WH Item no.: 9070792




Cover frame the Mura Theben WH Item no.: 9070798



Cover frame theMura FED WH Item no.: 9070786



Cover frame theMura LM WH





Adapter frame 45A MEMP CL



Adapter frame 45A GIST CL



Adapter frame 45A BJRE WH Item no.: 9070754



Item no.: 9080004



Item no.: 9080005



Adapter frame 45A BESI CL Item no.: 9080006



Adapter frame 45A BJBA CL Item no.: 9080002



Adapter frame 45A JUAS CL Item no.: 9080003



Adapter frame 45A BJRE CL

Item no.: 9080001



Item no.: 2060750



Accessories

Adapter frame 45A FEED CL Item no.: 9080007

